

Sub
at

1. A turbo decoder for performing decoding using results obtained by decoding a received signal, and subsequently repeating decoding a set number of times using results of decoding obtained successively, comprising:
- an error detector for detecting errors in results of decoding in parallel with a decoding operation; and
- a controller which, when absence of error has been detected, is operable for outputting results of decoding and halting the decoding operation even if number of times decoding has been performed has not attained said set number of times.
2. A turbo decoder according to claim 1, wherein said controller monitors the number of times errors are detected in decoded results when decoding has been performed said set number of times and executes the decoding operation further if the number of times errors are detected is equal to or less than the set value.
3. A turbo decoder for executing second decoding processing using results of decoding, which are obtained by applying first decoding processing to a received signal, and another received signal, executing the first decoding processing using second results of decoding and said received signal, executing the second decoding processing using first results of decoding and said other received signal, and subsequently executing the first and second decoding processing repeatedly,

comprising:

one elementary decoder for executing said first and second decoding processing;

a selection circuit for selecting, and inputting to
5 the elementary decoder, a prescribed received signal depending upon whether the first or the second decoding processing is executed;

interleaving means for interleaving the first results of decoding;

10 deinterleaving means for deinterleaving the second results of decoding; and

changeover means for inputting the first and second results of decoding to the elementary decoder via the interleaving means or the deinterleaving means.

15 4. A turbo decoder for receiving first data, second data obtained by encoding said first data, and third data obtained by interleaving and then encoding said first data, as signals ya, yb and yc, respectively, and executing decoding processing repeatedly using these
20 received signals, comprising:

first and second elementary decoders for executing second decoding processing using results of decoding, which are obtained by applying first decoding processing to prescribed received signals ya, yc, and the other
25 received signal yb, and subsequently executing, repeatedly, first decoding processing using second results of decoding and said received signals ya, yc, and second decoding processing using first results of

TOP SECRET

Sub
a1

Sub
al

decoding and said other received signal yb;

an interleaving unit for interleaving the received signal ya and the second results of decoding and inputting the same to the first elementary decoder

5 together with the received signal yc; and

a deinterleaving unit for deinterleaving the first results of decoding and inputting the same to the second elementary decoder together with the received signal yb;

10 wherein results of decoding are output from said second elementary decoder.

5. A turbo decoder for receiving first data, second data obtained by encoding said first data, and third data obtained by interleaving and then encoding said first data, as signals ya, yb and yc, respectively, and
15 executing decoding processing repeatedly using these received signals, comprising:

one elementary decoder for executing second decoding processing using results of decoding, which are obtained by applying first decoding processing to a
20 received signal, and another received signal, and subsequently executing, repeatedly, first decoding processing using second results of decoding and said received signal, and second decoding processing using first results of decoding and said other received
25 signal;

an interleaving unit for interleaving the received signal ya and inputting the same to the elementary decoder;

09901295-070901
T06070"562T0660

Suhail

means for deinterleaving results of the first decoding processing, interleaving results of the second decoding processing and inputting the deinterleaved and interleaved results to the elementary decoder.

15 first and second elementary decoders for executing
second decoding processing using results of decoding,
which are obtained by applying first decoding processing
to a prescribed received signal, and another received
signal, and subsequently executing, repeatedly, first
20 decoding processing using second results of decoding and
said received signal, and second decoding processing
using first results of decoding and said other received
signal; and

wherein the nature of an error generation pattern in decoded data finally output is controlled by

[illegible]

first and second elementary decoders for executing
second decoding processing using results of decoding,
which are obtained by applying first decoding processing
10 to a received signal, and another received signal, and
subsequently executing, repeatedly, first decoding
processing using second results of decoding and said
received signal, and second decoding processing using
first results of decoding and said other received
15 signal; and

wherein the nature of an error generation pattern in decoded data is controlled by switching the received signals input to the first and second elementary decoders.

8. A turbo decoder for performing decoding using results obtained by decoding a received signal, and subsequently repeating decoding a set number of times

Sub

10

15

20

add
a